



This is a popular antenna design as the performance is very good across the HF bands and requires little or no tuning. It's a dipole fed off center with a 4:1 current balun at the offset feedpoint. The antenna covers 80-10 meters but 15 meters and WARC bands are typically only available with an antenna tuner.

Design Parameters

For an 80-10 meter OCF dipole antenna, divide the $\frac{1}{2}$ wavelength standard of 468 by the lowest operating frequency of 3.6 MHz and you arrive at an overall length of 130'. This is the length of a standard dipole but instead of dividing the result in half, use a 36/64% offset to determine the feedpoint.

The total length of 130' multiplied by 0.64 (64%) gives the long leg length of 83.2 feet. The short leg length is the remainder or 46.8 feet. If you prefer, you can also correct the length based on the velocity factor of the wire (.975) although this generally does not make a noticeable difference in the antenna performance.

Using a quality 4:1 current balun at the feedpoint (**Balun Designs** Model 4115ocf, 4114ocf or 4113et) is crucial to the overall performance of the antenna. The feedpoint impedance at the offset is at or about 200 Ohms and the balun will provide good transformation to the coax feedline impedance of 50 Ohms.

To build the OCF dipole cut a single length of wire to an overall size of 133'. Next, cut the 133' into two separate lengths of 85' 2 1/2" and 47' 9 1/2". Strip one end of each length, install through the balun strain relief and solder to the connector at the balun. Now install the other end of each wire through the end insulators but leave 1 foot of wire dangling from the short length and 2 feet of wire dangling from the long length. This extra wire will be used to fine-tune the OCF after you install it. The antenna can be installed in an inverted V configuration keeping in mind that this design changes the feedpoint impedance and will tune differently.

After installing the OCF, check the resonant frequency or lowest SWR for 80 meters. It should be in the low portion of the 80 meter band (e.g., 3.5 MHz or lower). Now you can begin trimming small lengths of wire off each end of the OCF to obtain the lowest SWR at 3.6 MHz. Begin with no more than 6 inches off the long leg. **Be sure to trim each wire proportionately.** For example, if you cut 6 inches off the long leg, cut only 3 inches off the short leg. Depending on your surroundings and antenna height, 80m may only reach an SWR of approximately 1.8 – 2.2. This is normal and the higher bands will be lower.

This antenna has been calculated using 14 AWG stranded copper wire, with the jacket on. If you use bare twisted or solid copper wire, the lengths may change slightly.